

## RESIDENTIAL AND NON-RESIDENTIAL CHECKLIST FOR PERMITTING ELECTRIC VEHICLE SERVICE EQUIPMENT (EVSE)

Please complete the following information related to permitting and installation of Electric Vehicle Service Equipment (EVSE) as a supplement to the application for a building permit. This checklist contains the technical aspects of EVSE installations and is intended help expedite permitting and use for electric vehicle charging.

Upon this checklist being deemed complete, a permit shall be issued to the applicant. However, if it is determined that the installation might have a specific adverse impact on public health or safety, additional verification will be required before a permit can be issued.

This checklist substantially follows the "Plug-In Electric Vehicle Infrastructure Permitting Checklist" contained in the Governor's Office of Planning and Research "Zero Emission Vehicles in California: Community Readiness Guidebook" and is purposed to augment the guidebook's checklist.

Job Address:		Permit #:
Project 1	Гуре	
☐ Single-Family	Comr	mercial (Single Business)
☐ Multi-Family (Apartment)	Comr	mercial (Multi-Businesses)
☐ Multi-Family (Condominium)	☐ Mixed	d-Use
	Public	c Right-of-Way
Location and Number of EVSE to be Installed:		
Garage: Parking Level(s):	Parking Lot: Street Curb:	
Applicant Name:		
Applicant Phone & email:		
Contractor Name:	License # &	Туре:
Contractor Phone & email:		
Owner Name:		
Owner Phone & email:		



## RESIDENTIAL AND NON-RESIDENTIAL CHECKLIST FOR PERMITTING ELECTRIC VEHICLE SERVICE EQUIPMENT (EVSE)

EVSE Charging Level:			
Level 1 (120V)	Level 2 (240V) Level 3 (480V)		
Maximum Rating (Nameplate) of EV Service Equipment = kW			
Voltage EVSE =V	Manufacturer of EVSE:		
Mounting of EVSE:			
☐ Wall Mount ☐	Pole Pedestal Mount		
System Voltage:	NA 1900 N. J		
120/240V, 1φ, 3W 120/208V, 3φ, 4W 120/240V, 3φ, 4W			
<b>277/480V</b> , 3φ, 4W <b>O</b> tl	ther		
Rating of Existing Main Electrical Service Equipment = Amps			
Rating of Panel Supplying EVSE (if not directly from Main Service) = Amps			
Rating of Circuit for EVSE: Amps / Poles			
AIC Rating of EVSE Circuit Breaker (if not Single Family, 400A) = A.I.C. (or verify with Inspector in field)			
Specify either Connected, Calculated or Documented Demand Load of Existing Panel:			
Connected Load of Existing Panel Supplying EVSE = Amps			
Calculated Load of Existing	g Panel Supplying EVSE = Amps		
Demand Load of Existing Panel or Service Supplying EVSE = Amps (Provide Demand Load Reading from Electric Utility)			
Total Load (Existing plus EVSE	Load) = Amps		



## RESIDENTIAL AND NON-RESIDENTIAL CHECKLIST FOR PERMITTING ELECTRIC VEHICLE SERVICE EQUIPMENT (EVSE)

For Single Family Dwellings, if Existing Load is not known by any of the above methods, then the Calculated Load may be estimated using the "Single-Family Residential Permitting Application Example" in the Governor's Office of Planning and Research "Zero Emission Vehicles in California: Community Readiness Guidebook" https://www.opr.ca.gov

EVSE Rating Amps x 1.25 = Amps
Minimum Type/Size of EVSE Conductor = # AWG Conductor Type:
For Single-Family:
Size of Existing Service Conductors: # AWG/kcmil; or
Size of Existing Feeder Conductor Supplying EVSE: # AWG/kcmil
Conductor Type:
(or Verify with Inspector in field)
I hereby acknowledge that the information presented is a true and correct representation of existin conditions at the job site and that any causes for concern as to life-safety verifications may require further substantiation of information.
Signature of Permit Applicant: Date: